



IR55

Infrared Connection Module

Information and Installation Guide

v 1.2

IR55 Features

- * Easy to install, easy to use!
- * No maintenece or adjustments
- *Connect up to 10 infrared receivers
- *Connect up to 8 emitters (four I R34 double emitters)
- *Connect a PS1202 or PS1205 power supply

Specifications

I nfrared carrier frequency: 30-60kHz Power requirements: PS1202 200mA or PS1205 500mA unregulated 12VDC power supply Dimensions: 2-1/2" w x 1" h x 2-5/8" D (63 x 26 x 67mm). Color: Black Installation Tips:

1. Follow all local electrical & building code requirements.

The I R55 is usually positioned behind the stereo components it is helping to control.
Connect all of the infrared receivers in parallel to the I R55 blue three terminal connector as shown in the diagram. Wires can be solid or stranded, shielded or unshielded with a minimum of 24 gauge for runs under 200', 22 gauge for runs under 500' and 20 gauge for runs up to 1000'. Wires can be looped from I R21a to I R21a or home run. Home runs generally offer more reliability and future flexibility.

4. Connect the emitters by inserting their plugs into any available I R55 emitter jack. Up to four single emitter or double emitters (maximum eight emitters) can be connected to a single I R55. I f more emitter connections are required, call Knöll for amplified connection block information. 5. Lastly plug the PS1202 or PS1205 power supply into the I R55 and test the whole system.

Warranty

Knoll Systems warrants its products sold in the USA by authorized Knoll Systems dealers to be free from defects in materials and workmanship. The warranty extends for two full years from the date of purchase by the original consumer. Any products returned within the warranty period will be repaired or replaced at Knoll Systems option, at no cost. Knoll Systems will not be responsible for the actual cost of removal or reinstallation of the product, nor of any incidental or consequential damages. Some states do not allow the exclusion or limitation of incidental or consequential damages, so the above limitations may not apply to you. This warranty gives you specific legal rights. You may have additional legal rights that vary from state to state.

Knoll Systems 145 Tyee Drive Point Roberts, WA 98281

